

# Pocket Toner® NX8 Voice and Video Pro Kit

Test voice, data and video cables for open and short circuits, continuity and voltage

Quickly and easily test coax, telephone, home theater, audio, video, security and fire cables for continuity, AC and DC voltage, shorts, opens and 50-75  $\Omega$  termination-8x faster with 8 ID caps.

Simply place each of the numbered ID caps on the remotes ends of the cables to test. Then, quick-connect the main unit to the other end of the test cable one at a time. If there is continuity, the green LED on the ID cap will light and the main unit will show the ID cap's number (1-8) on its digital display. In addition, the audible indicator in the main unit will emit a brief tone. PTNX8 also tests for and displays the presence of

AC and DC voltages from 6v-52v.

### **Features**

- Test cables 8x faster with 8 ID caps--with LED to indicate continuity
- Low-voltage circuit protection (6v-52v) in main unit, toner unit and ID caps
- Eight segment LED displays five different test results
- Main unit "beeps" when line condition changes
- Bi-gender toner unit with removable Speed 81<sup>™</sup> coupler
- Two buzzers to indicate continuity
- Test for dial tone and polarity with the Dial Tone Detective™
- Auto shut-off feature extends battery life
- One-year limited warranty

## What's in the kit

- Pocket Toner® NX8
- 8 ID caps
- 66 block adapters
- RJ-11 adapter
- RJ-45 adapter
- Dial Tone Detective™
- Alligator clips and RJ-45 adapter
  AAA battery
- BNC-male adapter
- BNC-female adapter

- RCA-male adapter
- RCA-female adapter
- F-female coupler (F-81)
- F-male coupler (F-71)
- F-female coupler (Speed 81<sup>™</sup>)
- F-male push-on adapter
- Deluxe case with belt clip
- 8 RJ-11 adapters



## **Test Results Display**



Blinking [-] indicates an



Blinking [S]



Solid [C] indicates continuity with either a 50-75 ohm ID cap or the toner



A solid matching number indicates continuity with one of the 8 ID caps



Blinking [/] indicates AC voltage (>6 volts) Solid [4] indicates

open circuit







## PN# PTNX8-VV-PRO

networks





**Satellite** 



Audio & Video





Voice



Security & Fire



Cable & Telephone



**Professional** 

For more information: www.flukenetworks.com/PT